



POWERED by
HONDA



Total harmonic distortion 6%



Engine



Alternator and Frame

PRODUCT DETAILS

The Welling and Crossley P8000 is a 8kVA portable capacitor-type generator with E-start and 2 x 15 Amp 230V outlets.

Powered by a Honda petrol engine with electric start, it is the perfect size for almost everything.

The Honda Australia approved GX390 engine is known and respected as a reliable workhorse, enabling this generator to run your power tools, compressor, a welder and much more.

APPLICATIONS

- DIY workshops to power small to medium tools and lights
- Home back-up solution for essential appliances
- Outdoor events for lights, sound systems, etc.
- Mobile businesses or market stalls for powering appliances*

**Ensure generator noise levels comply with site-specific requirements and local regulations.*

FEATURES

- 2 x single-phase 15 Amp outlets
- Recoil start, electric start
- Powerful & efficient: Honda Australia approved air-cooled GX390 OHV 4-stroke engine
- CDI Magneto ignition
- Low oil-level shutdown
- 2-year Welling & Crossley warranty (battery excluded)

TECHNICAL DATA

POWER RATING	8.0 kVa
ALTERNATOR RATING	9.5 kVa
RATED VOLTAGE	230/240VAC 1ph 50Hz
RATED OUTPUT	Max. 15A
RATED MOTOR SPEED	3000 rpm
ENGINE MODEL	HONDA GX390
ENGINE TYPE	Single cylinder, 4-stroke, OHV, air-cooled petrol
DISPLACEMENT	389cc
OIL	1.1 litres SAE10W-40SE or SF

SPARK PLUG	NGK BPR6ES
NOISE LEVEL @ 7M	74 dBA
FUEL TYPE	Petrol – 91 octane unleaded
FUEL TANK CAPACITY	6.1 L
FUEL CONSUMPTION	Approx. 2.58L/hr @ 80% load
OPERATION HOURS	2.36 hrs at 80% load
PACKAGING (L X W X H)	820 x 550 x 562mm
PRODUCT (L X W X H)	810 x 545 x 545mm
DRY WEIGHT	85 kg