



LEADER 400 START 230V 12-24V



12V

24V

Overview

LEADER 400 START 230V 12-24V

cod. 807551

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage, and starting all types of petrol-driven and diesel-driven vehicles, up to 70 hp.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- display of charging and starting current
- protection against overloads and polarity reversal.



1 PH 230V



SMALL VAN



CE MARKING



CAR



TRUCK



EAC CERTIFICATION



BOAT



EXCAVATOR



TÜV SUD CERTIFICATION



TRACTOR



VAN

Technical data



CODE 807551



EFFECTIVE CHARGING CURRENT 45 A



ADJUSTMENT POSITIONS 3



SINGLE PHASE MAINS VOLTAGE 230 V



RATED CHARGE CURR. EN60335-2-29
30 A



DIMENSIONS 26,5 - 34,5 - 23 cm



MAINS FREQUENCY 50 - 60 Hz












START CURRENT 1V/C EN60335-2-29
180 A



WEIGHT 10,9 kg



LEADER 400 START 230V 12-24V

 CHARGE POWER 1 KW	 MAX STARTING CURRENT 300 A	 EAN CODE 800489764804 0
 START POWER 6,4 KW	 MIN. RATED REFERENCE CAPACITY 20 Ah	 PIECES/PALLET 27 pz/pallet
 CHARGING VOLTAGE 12 / 24 V	 MAX RATED REFERENCE CAPACITY 700 Ah	 PIECES/PALLET - B 36 pz/pallet - B

Included Accessories

-  CABLE 10 MMQ 2 M - 123425
-  COLORADO 150R POSITIVE CLAMP 150A - 712002
-  COLORADO 150B WORK CLAMP 150A - 712001