



## PRODUCT DETAILS

The Welling and Crossley P8750 is an AVR (automatic voltage regulated) generator with E-start. Supplied with transport kit (handles and wheels), this generator is Euro 5 emissions compliant. The generously sized 25L fuel tank and economical motor allow longer run times. The WC-P8750 packs a lot of power in a compact footprint.

## APPLICATIONS

- DIY workshops to power small to medium tools and lights
- Home back-up solution for essential appliances
- Outdoor events for lights, sound systems, etc.
- Mobile businesses or market stalls for powering small appliances

## FEATURES

- 2 x IP66 outlets (single phase – 15 Amp)
- USB-A and USB-C outlets
- Multiple start options: Recoil start, push-button electric start, wireless remote start, 2-wire remote start
- Transport kit included: Fold-out, wheelbarrow-style handle and large wheels
- Powerful & efficient: Air-cooled, OHV, 4-stroke engine with large fuel tank
- Digital V/F/T Display (Volts, Frequency, Time)
- Transistorised ignition
- Low-oil alarm, overload alarm, output indicator
- 2-year Welling & Crossley warranty (battery excluded)



Total harmonic distortion 6–8%



## TECHNICAL DATA

MODEL RATING	8.75kVa with AVR
POWER FACTOR	0.8
MAX. AC OUTPUT	7000 W
RATED AC OUTPUT	6800W Max. 15A
RATED MOTOR SPEED	3000 rpm
RATED VOLTAGE	230/240VAC 1ph 50Hz
ENGINE MODEL	WC-420: Euro 5 emissions compliant
ENGINE TYPE	Single cylinder, 4-stroke, OHV, air-cooled petrol
DISPLACEMENT	420cc

OIL	1.1 litres SAE10W-30
SPARK PLUG	Torch F6TC, Champion RN9YC
NOISE LEVEL @ 7M	72 dBA
FUEL TYPE	Petrol – 91 octane unleaded
FUEL TANK CAPACITY	25 L
FUEL CONSUMPTION	Approx. 1.48L/hr @ 1/4 load
PACKAGING (L X W X H)	710 x 535 x 590mm
PRODUCT (L X W X H)	700 x 660 x 600mm
DRY WEIGHT	90 kg