



CARAVANS  
& RV'S



CAMPING AND  
RECREATION



HOME  
BACKUP



MARKET STALLS  
MOBILE BUSINESS



SMALL OUTDOOR  
EVENTS



DIY  
WORKSHOP



'Pure Sine Wave' output.

Total harmonic distortion <3%

Suitable for powering sensitive  
electronics and medical devices



## PRODUCT DETAILS

The Welling and Crossley P6000Si is a Smart Silent Inverter type generator – the ideal companion for camping or outdoor adventures, home essential backup or general home handyman tasks. The highly efficient Euro 5 certified motor and advanced inverter technology provides stable, clean power for sensitive electronics. The intelligent idle control optimises fuel efficiency and reduces noise. The P6000SI is fitted with a retractable handle and wheels for ease of transportation and storage. Enjoy the convenience of a full-colour LCD display and quick-charge USB ports next time you're off the grid.

## APPLICATIONS

- Quiet and efficient power for stalls, or outdoor entertainment equipment
- Back-up solution for to keep your home appliances powered during outages
- Best performance when providing power for steady loads with little surge or in-rush current demand

## FEATURES

- 1 x IP44 outlet (single phase – 15 Amp)
- 1 x IP66 outlet (single phase – 32 Amp)
- 1 x USB-A 18W
- 1 x USB-C 15W
- E-start, Wireless and Recoil starting
- 2-wire start connection
- Acoustic casing with forced fan cooling
- Low-oil alarm, overload alarm, output indicator
- LCD digital display: Comprehensive information at a glance for easy monitoring and operation
- 2-year Welling and Crossley warranty (battery excluded)

## TECHNICAL DATA

|                   |                                                                     |
|-------------------|---------------------------------------------------------------------|
| MODEL             | WC-P6000SI                                                          |
| MAX. AC OUTPUT    | 6000 W                                                              |
| RATED AC OUTPUT   | 5500W Max. 22.9A                                                    |
| RATED MOTOR SPEED | 3000 rpm                                                            |
| RATED VOLTAGE     | 240VAC 1ph / 50Hz                                                   |
| ENGINE MODEL      | WC-320B: Euro 5 emissions compliant                                 |
| ENGINE TYPE       | Single cylinder, 4-stroke, OHV, fan-forced, air-cooled petrol motor |
| IGNITION SYSTEM   | Transistor                                                          |
| DISPLACEMENT      | 322cc                                                               |

|                       |                              |
|-----------------------|------------------------------|
| OIL                   | 0.7 litre SAE10W-30          |
| SPARK PLUG            | TORCH F7RTC                  |
| NOISE LEVEL @ 7M      | 64 dBA                       |
| FUEL TYPE             | Petrol – 91 octane unleaded  |
| FUEL TANK CAPACITY    | 13.5 L                       |
| FUEL CONSUMPTION      | Approx. 1.35 L/hr @ 1/4 load |
| PACKAGING (L X W X H) | 665 x 525 x 560mm            |
| PRODUCT (L X W X H)   | 640 x 480 x 550mm            |
| DRY WEIGHT            | 57.5 kg                      |