



LEADER 220 START 230V



Overview

LEADER 220 START 230V

cod. 807539

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage, and starting all types of petrol-driven vehicles.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- display of charging and starting current
- protection against overloads and polarity reversal.



1 PH 230V



SMALL VAN



CE MARKING



CAR



TRUCK



EAC CERTIFICATION



BOAT



EXCAVATOR



TÜV SUD CERTIFICATION



TRACTOR



VAN

Technical data



CODE 807539



EFFECTIVE CHARGING CURRENT 30 A



ADJUSTMENT POSITIONS 2



SINGLE PHASE MAINS VOLTAGE 230 V



RATED CHARGE CURR. EN60335-2-29
20 A



DIMENSIONS 22,5 - 29 - 20,5 cm



MAINS FREQUENCY 50 - 60 Hz












START CURRENT 1V/C EN60335-2-29
120 A



WEIGHT 9 kg



LEADER 220 START 230V

| | | |
|---|---|--|
|  CHARGE POWER 0,8 KW |  MAX STARTING CURRENT 180 A |  EAN CODE 800489788516 2 |
|  START POWER 3,6 KW |  MIN. RATED REFERENCE CAPACITY 30 Ah |  PIECES/PALLET 56 pz/pallet |
|  CHARGING VOLTAGE 12 / 24 V |  MAX RATED REFERENCE CAPACITY 400 Ah |  PIECES/PALLET - B 42 pz/pallet - B |

Included Accessories

CABLE 6 MMQ 2 M AND WORK CLAMP - 123569

CABLE 6MMQ 2 M POSITIVE CLAMP - 123588